

PRODUCT-DETAILS

# MS116-10

## MS116-10 Manual Motor Starter



### General Information

Extended Product Type	MS116-10
Product ID	1SAM250000R1010
EAN	4013614320330
Catalog Description	MS116-10 Manual Motor Starter
Long Description	The MS116-10 manual motor starter (also known as motor protection circuit breaker or manual motor protector) is a compact 45 mm width device with a rated operational current of $I_e = 10.0$ A. This device is used to manually switch on and off motors and to protect them reliably and without the need for a fuse from short-circuits, overload and phase failures. The manual motor starter offers a rated service short-circuit breaking capacity $I_{cs} = 50$ kA at 400 VAC and trip class 10A.

### Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85362010

### Popular Downloads

Data Sheet, Technical Information	2CDC131025D0201
Instructions and Manuals	2CDC131011M6802
Instructions and Manuals (Part 2)	2CDC131060M0202
Time-Current	1SAM200505F0010

## Characteristic Curve

I <sup>2</sup> t Characteristic	1SAM200507F0001 1SAM200507F0002 1SAM200507F0003
Cut-off Current Characteristic	1SAM200508F0001 1SAM200508F0002 1SAM200508F0003
Dimension Diagram	1SAM200422F0001

## Dimensions

Product Net Width	45 mm
Product Net Height	90 mm
Product Net Depth / Length	85.6 mm
Product Net Weight	0.265 kg

## Technical

Rated Service Short-Circuit Breaking Capacity (I <sub>cs</sub> )	(230 V AC) 50 kA (400 V AC) 50 kA (440 V AC) 6 kA (500 V AC) 6 kA (690 V AC) 2 kA
Rated Ultimate Short-Circuit Breaking Capacity (I <sub>cu</sub> )	(230 V AC) 50 kA (400 V AC) 50 kA (440 V AC) 18 kA (500 V AC) 10 kA (690 V AC) 3 kA
Rated Instantaneous Short-Circuit Current Setting (I <sub>i</sub> )	150 A
Setting Range	6.3 ... 10 A
Rated Operational Power AC-3 (P <sub>e</sub> )	(400 V) Three Phase 4 kW
Rated Operational Voltage	Main Circuit 690 V AC
Rated Operational Current (I <sub>e</sub> )	10 A
Rated Operational Current AC-3 (I <sub>e</sub> )	10 A
Rated Frequency (f)	Main Circuit 50 Hz Main Circuit 60 Hz
Rated Impulse Withstand Voltage (U <sub>imp</sub> )	Main Circuit 6 kV
Rated Insulation Voltage (U <sub>i</sub> )	690 V
Power Loss	at Rated Operating Conditions per Pole 0.9 ... 2.4 W
Number of Poles	3
Conventional Free-air Thermal Current (I <sub>th</sub> )	Main Circuit 10 A
Degree of Protection	Housing IP20 Main Circuit Terminals IP10
Pollution Degree	3
Electrical Durability	100000 cycle
Mechanical Durability	100000 cycle
Terminal Type	Screw Terminals
Connecting Capacity Main Circuit	Flexible with Ferrule 1/2x 0.75 ... 2.5 mm <sup>2</sup> Flexible with Insulated Ferrule 1/2x 0.75 ... 2.5 mm <sup>2</sup> Flexible 1/2x 0.75 ... 2.5 mm <sup>2</sup> Rigid 1/2x 1 ... 4 mm <sup>2</sup>
Tightening Torque	Main Circuit 0.8 ... 1.2 N·m

Wire Stripping Length	Main Circuit 9 mm
Recommended Screw Driver	Pozidriv 2
Mounting Position	Position 1 to 6
Mounting on DIN Rail	TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715
Minimum Mounting Distance	Electrical Conductive Board, Horizontal - Up to 400 V 0 mm Electrical Conductive Board, Horizontal - Up to 690 V 1.5 mm Electrical Conductive Board, Vertical 75 mm Other Device Same Type, Horizontal 0 mm Other Device Same Type, Vertical 150 mm
Actuator Type	Rotary Handle
Contact Position Indication	ON / OFF
Standards	IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1

## Technical UL/CSA

Short-Circuit Current Rating (SCCR)	Any UL Listed Fuses or Circuit-Breakers, Group Installations (480 V AC) 18 kA Any UL Listed Fuses or Circuit-Breakers, Group Installations (600 V AC) 5 kA Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (480 V AC) 18 kA Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (600 V AC) 5 kA
Maximum Operating Voltage UL/CSA	Main Circuit 600 V AC
Ampere Rating UL/CSA	10 A
Horsepower Rating UL/CSA	(200 V AC) Three Phase 2 Hp (208 V AC) Three Phase 2 Hp (220 ... 240 V AC) Three Phase 3 Hp (440 ... 480 V AC) Three Phase 5 Hp (550 ... 600 V AC) Three Phase 7.5 Hp
Full Load Amps Motor Use	(200 V AC) Three Phase 7.8 A (208 V AC) Three Phase 7.5 A (220 ... 240 V AC) Three Phase 9.6 A (440 ... 480 V AC) Three Phase 7.6 A (550 ... 600 V AC) Three Phase 9 A
Locked Rotor Amps	(200 V AC) Three Phase 57.5 A (208 V AC) Three Phase 55 A (220 ... 240 V AC) Three Phase 64 A (440 ... 480 V AC) Three Phase 46 A (550 ... 600 V AC) Three Phase 50.8 A
General Use Rating UL/CSA	(600 V AC) 10 A
Connecting Capacity Main Circuit UL/CSA	Flexible 1/2x 16-12 AWG Stranded 1/2x 16-12 AWG
Tightening Torque UL/CSA	Main Circuit 10 in-lb

## Environmental

Ambient Air Temperature	Around the Enclosure 0 ... +40 °C Operation -25 ... +70 °C Operation Compensated -25 ... +55 °C Storage -50 ... +80 °C
Ambient Air Temperature Compensation	Yes
Maximum Operating Altitude Permissible	2000 m
Resistance to Shock acc.	11 ms Pulse 25g

to IEC 60068-2-27

Resistance to Vibrations  
acc. to IEC 60068-2-6

5g / 3 ... 150 Hz

RoHS Status

Following EU Directive 2011/65/EU

---

**Certificates and Declarations (Document Number)**


---

ABS Certificate	1SAA963000-0104
BV Certificate	1SAA963000-0204
CB Certificate	1SAA963000-2003
CCC Certificate	1SAA963000-3804
cUL Certificate	cUL_E137861
Cut-off Current Characteristic	1SAM200508F0001 1SAM200508F0002 1SAM200508F0003
Declaration of Conformity - CE	1SAD938521-0060
DNV Certificate	1SAA963000-0303
DNV GL Certificate	1SAA963000-0303
EAC Certificate	1SAA963000-2701
Environmental Information	1SAA963001-2401
GL Certificate	1SAA963000-0402
GOST Certificate	1SAA963001-2702
I <sup>2</sup> t Characteristic	1SAM200507F0001 1SAM200507F0002 1SAM200507F0003
Instructions and Manuals	2CDC131011M6802
Instructions and Manuals (Part 2)	2CDC131060M0202
KC Certificate	1SAA963000-1501
LR Certificate	1SAA963000-0505
RMRS Certificate	1SAA918000-0704
RoHS Information	1SAD938517-0060
Time-Current Characteristic Curve	1SAM200505F0010
UL Certificate	UL_E137861

---

**Container Information**


---

Package Level 1 Units	box 1 piece
Package Level 1 Width	92 mm
Package Level 1 Depth / Length	95 mm
Package Level 1 Height	50 mm
Package Level 1 Gross Weight	0.28 kg
Package Level 1 EAN	4013614320330
Package Level 2 Units	carton 40 piece
Package Level 2 Width	280 mm
Package Level 2 Depth / Length	395 mm
Package Level 2 Height	210 mm
Package Level 2 Gross Weight	11.586 kg
Package Level 2 EAN	4013614408700

## Classifications

Object Classification Code	F
ETIM 4	EC000074 - Motor protective circuit-breaker
ETIM 5	EC000074 - Motor protective circuit-breaker
ETIM 6	EC000074 - Motor protection circuit-breaker
ETIM 7	EC000074 - Motor protection circuit-breaker
eClass	7.0 27370401
UNSPSC	39121521
IDEA Granular Category Code (IGCC)	4845 >> 3 Pole Motor Circuit Protector Circuit Breakers
E-Number (Sweden)	3111948

## Accessories

Identifier	Description	Type	Quantity	Unit Of Measure
1SAM201901R1001	HKF1-11 Hilfskontakt	HKF1-11	1	piece
1SAM201901R1201	HKF1-11K Hilfskontakt	HKF1-11K	1	piece
1SAM201901R1002	HKF1-20 Hilfskontakt	HKF1-20	1	piece
1SAM201901R1202	HKF1-20K Hilfskontakt	HKF1-20K	1	piece
1SAM201901R1004	HKF1-01 Hilfskontakt	HKF1-01	1	piece
1SAM201901R1003	HKF1-10 Hilfskontakt	HKF1-10	1	piece
1SAM201902R1002	HK1-20 Hilfskontakt	HK1-20	1	piece
1SAM201902R1202	HK1-20K Hilfskontakt	HK1-20K	1	piece
1SAM201902R1001	HK1-11 Hilfskontakt	HK1-11	1	piece
1SAM201902R1201	HK1-11K Hilfskontakt	HK1-11K	1	piece
1SAM201902R1003	HK1-02 Hilfskontakt	HK1-02	1	piece
1SAM201902R1203	HK1-02K Hilfskontakt	HK1-02K	1	piece
1SAM201902R1004	HK1-20L Hilfskontakt	HK1-20L	1	piece
1SAM201902R1204	HK1-20LK Hilfskontakt	HK1-20LK	1	piece
1SAM201903R1002	SK1-20 Signalkontakt	SK1-20	1	piece
1SAM201903R1202	SK1-20K Signalkontakt	SK1-20K	1	piece
1SAM201903R1001	SK1-11 Signalkontakt	SK1-11	1	piece
1SAM201903R1201	SK1-11K Signalkontakt	SK1-11K	1	piece
1SAM201903R1003	SK1-02 Signalkontakt	SK1-02	1	piece
1SAM201903R1203	SK1-02K Signalkontakt	SK1-02K	1	piece
1SAM201910R1001	AA1-24 Arbeitsstromauslöser	AA1-24	1	piece
1SAM201910R1002	AA1-110 Arbeitsstromauslöser	AA1-110	1	piece
1SAM201910R1003	AA1-230 Arbeitsstromauslöser	AA1-230	1	piece
1SAM201910R1004	AA1-400 Arbeitsstromauslöser	AA1-400	1	piece
1SAM201904R1010	UA1-20 Unterspannungsauslöser	UA1-20	1	piece
1SAM201904R1001	UA1-24 Unterspannungsauslöser	UA1-24	1	piece
1SAM201904R1002	UA1-48 Unterspannungsauslöser	UA1-48	1	piece
1SAM201904R1003	UA1-60 Unterspannungsauslöser	UA1-60	1	piece
1SAM201904R1004	UA1-110 Unterspannungsauslöser	UA1-110	1	piece
1SAM201904R1008	UA1-208 Unterspannungsauslöser	UA1-208	1	piece
1SAM201904R1005	UA1-230 Unterspannungsauslöser	UA1-230	1	piece
1SAM201904R1006	UA1-400 Unterspannungsauslöser	UA1-400	1	piece
1SAM201904R1007	UA1-415 Unterspannungsauslöser	UA1-415	1	piece
1SAM201904R1009	UA1-575 Unterspannungsauslöser	UA1-575	1	piece
1SAM201907R1101	S1-M1-25 3-Phasen Einspeiseblock	S1-M1-25	1	piece
1SAM201907R1102	S1-M2-25 3-Phasen Einspeiseblock	S1-M2-25	1	piece
1SAM201907R1103	S1-M3-25 3-Phasen Einspeiseblock	S1-M3-25	1	piece
1SAM201913R1103	S1-M3-35 3-Phasen Einspeiseblock	S1-M3-35	1	piece
1SAM201914R1002	S1-PB1-25 3-Phasen Einspeiseblock	S1-PB1-25	1	piece
1SAM201914R1001	PB1-1-32 Phasenverbinder	PB1-1-32	1	piece

1SAM201906R1102	PS1-2-0-65 3-Phasen Sammelschiene	PS1-2-0-65	1	piece
1SAM201906R1112	PS1-2-1-65 3-Phasen Sammelschiene	PS1-2-1-65	1	piece
1SAM201906R1122	PS1-2-2-65 3-Phasen Sammelschiene	PS1-2-2-65	1	piece
1SAM201916R1103	PS1-3-0-100 3-Phasen Sammelschiene	PS1-3-0-100	1	piece
1SAM201906R1103	PS1-3-0-65 3-Phasen Sammelschiene	PS1-3-0-65	1	piece
1SAM201916R1113	PS1-3-1-100 3-Phasen Sammelschiene	PS1-3-1-100	1	piece
1SAM201906R1113	PS1-3-1-65 3-Phasen Sammelschiene	PS1-3-1-65	1	piece
1SAM201916R1123	PS1-3-2-100 3-Phasen Sammelschiene	PS1-3-2-100	1	piece
1SAM201906R1123	PS1-3-2-65 3-Phasen Sammelschiene	PS1-3-2-65	1	piece
1SAM201916R1104	PS1-4-0-100 3-Phasen Sammelschiene	PS1-4-0-100	1	piece
1SAM201906R1104	PS1-4-0-65 3-Phasen Sammelschiene	PS1-4-0-65	1	piece
1SAM201916R1114	PS1-4-1-100 3-Phasen Sammelschiene	PS1-4-1-100	1	piece
1SAM201906R1114	PS1-4-1-65 3-Phasen Sammelschiene	PS1-4-1-65	1	piece
1SAM201906R1124	PS1-4-2-65 3-Phasen Sammelschiene	PS1-4-2-65	1	piece
1SAM201916R1105	PS1-5-0-100 3-Phasen Sammelschiene	PS1-5-0-100	1	piece
1SAM201906R1105	PS1-5-0-65 3-Phasen Sammelschiene	PS1-5-0-65	1	piece
1SAM201916R1115	PS1-5-1-100 3-Phasen Sammelschiene	PS1-5-1-100	1	piece
1SAM201906R1115	PS1-5-1-65 3-Phasen Sammelschiene	PS1-5-1-65	1	piece
1SAM201906R1125	PS1-5-2-65 3-Phasen Sammelschiene	PS1-5-2-65	1	piece
1SAM201908R1001	BS1-3 Schutzabdeckung	BS1-3	1	piece
GJF1101903R0001	SA1 - Schaltsperre	SA1	1	piece
GJF1101903R0002	SA2 - Vorhängeschloss	SA2	1	piece
GJF1101903R0003	SA3 - Vorhängeschloss	SA3	1	piece
1SAM201912R1010	DMS132-G Türmontagesatz	DMS132-G	1	piece
1SAM201912R1011	DMS132-Y Türmontagesatz	DMS132-Y	1	piece
1SAM201911R1012	IB132-F Gehäuse	IB132-F	1	piece
1SAM201911R1010	IB132-G Gehäuse	IB132-G	1	piece
1SAM201911R1011	IB132-Y Gehäuse	IB132-Y	1	piece
1SAM201909R1021	MSAH1 Wellenhalter	MSAH1	1	piece
1SAM201920R1000	MSH-AR Wellenführungsring	MSH-AR	1	piece
1SAM201920R1001	MSHD-LB Griff	MSHD-LB	1	piece
1SAM201920R1002	MSHD-LY Griff	MSHD-LY	1	piece
1SAM101923R0002	MSMN Mitnehmer	MSMN	1	piece
1SAM101923R0012	MSMNO Mitnehmer	MSMNO	1	piece
1SAM101924R0013	MSEX-30 Achse	MSEX-30	1	piece
1SAM101924R0003	MSEX-32 Achse	MSEX-32	1	piece
1SCA101647R1001	OXS6X85 Welle Länge 85mm Wellen-ø 6mm für Selektorgriffe	OXS6X85	1	piece
1SCA108043R1001	OXS6X105 Welle Länge 105mm Wellen-ø 6mm für Pistolengriffe	OXS6X105	1	piece
1SCA101655R1001	OXS6X130 Welle Länge 130mm Wellen-ø 6mm für Selektorgriffe	OXS6X130	1	piece
1SCA101659R1001	OXS6X180 Welle Länge 180mm Wellen-ø 6mm für Selektorgriffe	OXS6X180	1	piece
1SAM201909R1001	FS116 Schraubenbefestigungs-Kit	FS116	1	piece

---

## Categories

---

Low Voltage Products and Systems → Circuit Breakers → Manual Motor Starters

Low Voltage Products and Systems → Control Products → Manual Motor Starters → Manual Motor Starters

